



# MicroComm DXI


## AIB-400 Audio Input Board

### Description

The AIB-400 Audio Input Board installs in the card cage and provides up to eight external audio inputs. It is used to connect to auxiliary audio equipment such as microphones, tape players, radio tuners, two-way radios, and automatic message repeaters. Each input is balanced and transformer isolated, and responds to software controlled level adjustment and impedance matching.

### Features


- eight (8) audio input channels
- each input adjustable for mic level or line level
- independent software audio level controls for each channel
- 3 LEDs indicate operating status
- converts analog audio to internal digital format
- balanced inputs
- all field connections on rear of the card to expedite system set up and maintenance
- digital audio bus connections supply a redundant signal to an optional redundant control card
- fault protection on all input wiring
- live card insertion and removal to expedite installation and maintenance
- internal fuse protect circuitry
- status output controls and control input on each channel



### Specifications

Physical Form Factor	MicroComm DXI I/O Card
Environmental	
Operating Temperature	32 to 122 °F (0 to 50 °C)
Storage Temperature	-40 to 158 °F (-40 to 70 °C)
Humidity	0 to 95 % non-condensing
Power Supply	±12 Vdc ± 10% @ 2 A max provided by I/O Card Cage
Input Level	50 mVp-1 Vp
Input Impedance	10 K ohms
Field Connections	DB-50 with quick release lock
Input Capacity	8 channels
Cabling	
Audio Inputs	22 ga shielded twisted pair, max 2500 ft (750 m)
Standards	FCC Part 15

## Mechanical



## Ordering Information

Part number AIB-400

## Accessories

Field Interface Cable

CBL-120-A

Document # DS-AIB-400-1.4 • Copyright © 1999 Harding Instrument Co. Ltd. • All Specifications subject to change without notice • Printed in Canada



9564 Yellowhead Trail NW  
Edmonton, AB T5G 0W4  
sales@harding.ca

Tel 780.462.7100  
Fax 780.450.8396  
www.harding.ca



Represented by: